

AR

drOppel^{RF}[®]

ST-501



RADIO FREQUENCY ELECTROSURGICAL DEVICE

RF
SYSTEM

OB • GYN
Surgery (GS, OS, NS)
ENT
Dermatology • Urology

SOMETECH
SINCE 1989

RADIO FREQUENCY ELECTROSURGICAL DEVICE

What is the 4MHz Radio Frequency Surgical Unit?


Dr.Oppel's electrode is not being heated by itself. Electrode lets the cellular tissue produce the joule heat, and operates hemostasis, cutting, and coagulation. 4MHz radio frequency makes possible precise cutting and deep coagulation even in blood.

There is no carbonization and damages to the surrounding cellular tissue by electric spark, and the safety secured.

Specially developed various Bipolar and Monopolar electrodes for OB/GYN, PS/DER, Urology has outstanding performance in Micro Surgery by their excellent output time function.




The distinctive functions from other electrosurgical units and lasers



OB / GYN


Radio frequency coagulation for Cervical Erosion

► The mechanism of erosion cure




When columnar epithelium is defected in a special way, the erosion is cured by ingestion of the near squamous epithelium.

► Cause of residue and relapse of columnar epithelium in erosion cure



Since there are lots of unexpected cases when nabothian cysts are deeply formed in a patient's cervix, even though columnar epithelium is defected with drug, cauterization, and cryosurgery, the perfect cure is said to be hard due to the difficulty of ingestion of squamous epithelium resulting in insufficient removal of columnar epithelium. For perfect removal of erosion, 5mm depth of coagulation is needed.


► What is RF coagulation?



It's a way of coagulation necrosis to the 5mm depth of tissue, when the radio frequency current flows from electrode, passing tissue, to the patient plate, by producing joule heat on the tissue itself close to electrode. It's very hard to make necrosis with cauterization or cryosurgery because no deep coagulation is capable. However, coagulation necrosis is perfectly achieved in the coagulation with radio

frequency current because electrode lets the tissue itself produce joule heat.

► Coagulation range




First, insert Ø6mm semi-ball type electrode into the os to 1~1.5Cm depth and start coagulation until boiling noise is heard, and then rotate electrode and slide all areas of erosion. In addition, perform coagulation on the normal squamous epithelium of ectocervix region to be 2mm-5mm overlapped.

Caution


For 5mm depth coagulation without carbonization, please rub the part with the electrode.

► Self control of coagulation depth



The coagulative depth is decided by the electrode size and the device is designed to make different coagulation depth by the electrode size as above.

► Healing progress



► Pain during operation

- As a rule, no anesthesia is needed. At times, there are some patients who feel painful, but most are operated easily without anesthesia. Only nulliparous woman is occasionally needed for that.

► Late Bleeding

- If the coagulation depth is shallow, necrosis region could be not enough and bleeding could occur due to vascular exposure. In this case, columnar epithelium is still remaining and squamous epithelium isn't repaired. The important thing, in this case, is to perform coagulation to the 5mm depth with care in an early stage of the practice. In addition, warn the patient to be careful not to have necrosis region separate by exercise or sexual intercourse. Therefore, to prevent late bleeding, it is required that the necrosis region should be remaining without separation for 3 weeks until the blood vessel closes up.

► Side effects


- No report has been made about side effects such as infertility and atresia of cervix caused by excessive coagulation.

► Radio frequency conization for CIN lesion


► Special points

- Capable of a simple operation on an outpatient basis.
- Tissue sample is used for pathology reading.
- No general anesthesia is needed. Conization procedure takes only several seconds after local anesthesia. (10 seconds in conization and 3-4 minutes in coagulation).
- Various angles of conization probes.
- Perfect bleeding control.
- No suture is needed after conization.
- Short healing period (4-6 weeks).


► Radical Conization by HFSU



► Biopsy by conization




► Procedure of radical conization





- Firstly, place a patient on the operating table and carry out vaginal douche. And then, place the patient plate on the hip and expose the cervix. Secondly, after setting a conization electrode in the hand piece, start the conization from the part where no lesion is inferred to exist, and operate without a break. In this case, to proceed properly, cut by rotating conization electrode at 180 degrees, and then step off from the foot pedal. Continuously, keep operating the rest part of 180 degrees after changing handling form. After conization, coagulate the cut part widely by a Ø6mm bended semi-ball electrode. This is the purpose of necrosis after conization for the worry some where the lesion remains.

► Operation progress



- Different from laser treatment, radio frequency coagulation replaces the columnar epithelium with squamous epithelium completely in 4–6 weeks, also shown clearly in the colposcopy. Only small bleeding, but no massive one, may occur in the course of healing.

Electrodes



Electrodes Option




EU Type
 USA Type

※ Super Fine: Ø0.2 Tungsten Wire / Fine: Ø0.25 Tungsten Wire / Regular : Ø0.3 Tungsten Wire

Surgery (GS, OS, NS)


Nevus and freckle removal



- Vaporize by using needle electrode after setting timer for continuous and output power 8 ~ 9. It hardly leaves a scar since the surrounding tissues are not damaged.

Applicable electrodes : E06, J03

Wart, corn, condyloma and polyp removal




Applicable electrodes : K, L, N, O electrodes

- Resect by using loop electrode or diamond electrode after setting timer continuous and output power 6~8.

Operation of hemorrhoids (Internal, external hemorrhoids)

First or second degree early hemorrhoid :




Radio frequency coagulation without resection

- For early hemorrhoids, coagulate mucosa after setting the timer for 1 sec and output power 2~5.

Applicable electrodes : E03b, E04b

Second and third degree early hemorrhoids : Inside coagulation of mucosa by insulated bipolar electrodes



- Coagulate around hemorrhoidal plexus to reduce tissue volume without any damage to mucosa.

Applicable electrodes : T16 (Insulated bipolar electrode for inside coagulation of hemorrhoids)

Third or fourth degree hemorrhoids, strangulated hemorrhoids, mixed hemorrhoids and anal prolapse


- Operation by various electrodes for incision, hemostasis and excision of hemorrhoidal piles.

Applicable electrodes : E07, E09, J03, K02, K04



Osmidrosis axillae operation (Apocrine gland coagulation)


- Monopolar
- Timer : 1 second
- Output power : 7~8



Applicable electrodes : C10 (Insulated coagulation electrode (end cut flatly))

Hair root removal (Permanent removal)

- Monopolar
- Timer : 1/4 ~ 1/8 second
- Output power : 2~4



- It does not leave a scar since only hair root is coagulated without damage to skin.

Applicable electrodes : Hair root removal electrodes

Electrodes

C10

Ø1.0 Insulated coagulation electrode (1 Point curved, end cut flatly) for osmidrosis axilla

E03b

Ø4 Bended semi-ball(L90), Coagulation to 3mm depth

E04a

Ø3 Straight ball(L90), Coagulation to 2mm depth, rapid superficial coagulation

E04b

Ø3 Bended ball(L90), Coagulation to 2mm depth, rapid superficial coagulation

E06

Spire, Micro coagulation

E07

Blade(Curved), Hemostatic cutting and surface coagulation

E09

Blade (Straight), Hemostatic cutting and surface coagulation

J03

Ø0.3 Regular L15 Needle

J04

Ø0.3 Regular L15 Round Needle

K01

Super fine Ø4 Loop

K02

Super fine Ø6 Loop

K04

Fine Ø10 Loop

L02

Super Fine Ø0.2 L6 Diamond(Resection)

Electrodes Option

BS2510

Ø0.15 wire(Hair root removal)

BS3512

Ø0.15 wire(Hair root removal)

BS5025

Ø0.15 wire(Hair root removal)

BL4015

Ø0.18 wire(Hair root removal)

BL4515

Ø0.18 wire(Hair root removal)

BL5025

Ø0.18 wire(Hair root removal)

I18



Bipolar Cord


EU Type
USA Type

T16


Ø1.3 Insulated bipolar electrode for snoring (soft palate coagulation) and hemorrhoid

Inside coagulation of palate mucosa (Snoring)

- Bipolar • Timer : 1 second • Output power : 6



Operation procedure




Applicable electrodes : T16

Inside coagulation of inferior turbinate mucosa (Chronic hypertrophic rhinitis)

- Bipolar • Timer : 1 second • Output power : 6

Operation procedure



Applicable electrodes : T17

Electrodes Option

I18




Bipolar Cord

EU Type
 USA Type

Radio frequency perforation and drainage for exudative otitis media

- Monopolar • Timer : 1/4 second • Output power : 5~6

Operation procedure



Make a hole in ear drum by transmitting the radio frequency on the top of the insulated cutting needle and remove inflammatory discharges. The hole slightly coagulated will be cured soon naturally.

Applicable electrodes : J10

Electrodes


- E04a Ø3 Straight ball(L90), Coagulation to 2mm depth, rapid superficial coagulation
- E04b Ø3 Bended ball(L90), Coagulation to 2mm depth, rapid superficial coagulation
- E05a Ø2 Bended ball(L90), Epistaxis hemostasis
- E09 Blade (Straight), Hemostatic cutting and surface coagulation
- J03 Ø0.3 tungsten wire L15 Needle (Cutting)
- J04 Ø0.3 Regular L15 round Needle (Cutting)
- J10 Ø0.5 Stainless steel bended electrode (Ear drum perforation electrode for exudative otitis media)
- K02 Super Fine Ø0.2 Loop (Resection)
- K04 Fine Ø0.25 Loop (Resection)
- N04 Fine L8 Ø0.25 Oval Loop (Resection)
- T01 Bipolar cord (For "T" series)
- T16 Ø1.3 Insulated bipolar electrode for snoring treatment (soft palate ablation) and hemorrhoid
- T17 Ø1.3 Insulated electrode for tissue ablation of turbinate mucosa (for hypertrophic rhinitis)

※ Super Fine: Ø0.2 Tungsten Wire / Fine: Ø0.25 Tungsten Wire / Regular : Ø0.3 Tungsten Wire

Dermatology • Urology

Hair root removal (Permanent removal)

- After setting the unique timer function of Dr. Oppel 1/4~1/8 second, and output power 2~4, repeat treatment.



Applicable electrodes : Hair removal electrodes

ITEM NO	Shape	Color	Length of A	Length of B	External diameter of needle
BS2510		white	2.5mm	1.0mm	Ø0.15 wire
BS3512		Black	3.5mm	1.2mm	Ø0.15 wire
BS5025		Red	5.0mm	2.5mm	Ø0.15 wire
BL4015		Yellow	4.0mm	1.5mm	Ø0.18 wire
BL4515		Blue	4.5mm	1.5mm	Ø0.18 wire
BL5025		Green	5.0mm	2.5mm	Ø0.18 wire

Nevus and freckle removal



- Vaporize by using needle electrode after setting timer for continuous and output power 3.5~4.5. It hardly leaves a scar since the surrounding tissues are not damaged.


Applicable electrodes : E06, J03

Electrodes

C10	Ø1.0 Insulated coagulation electrode (end cut flatly) for osmidrosis axillae
E04	Ø3 Straight ball(Hemostatic coagulation)
E05	Ø2 Straight ball(Hemostatic coagulation)
E06	Spire(Micro coagulation)
E09	Blade (Straight), Hemostatic cutting and surface coagulation
E10b	Hemostatic cutting electrode for blepharoplasty (15mm)
J03	Regular L15 Needle(Incision, Vaporization)
J06	Super fine L5 bended Needle
J11	Micro cutting (2mm)
J12	Micro cutting (3mm)
K01	Super fine Ø4 Loop
K02	Super fine Ø6 Loop

Osmidrosis axillae operation (Apocrine gland coagulation)

- After setting the unique timer function of Dr. Oppel for 1 second and output power 7~8, repeat coagulation to the target area in order.




Applicable electrodes : C10

(Side view)
(Bottom view)

Wart, corn, condyloma and polyps removal


- Continuous
- Output power : 6~8



Applicable electrodes : K01, K02

- Resect by using loop electrode or diamond electrode.

Circumcision



- Various types of posthotomy can be fulfilled with the various kinds of electrodes excellent in pure cutting and coagulation.

Electrodes Option

BS2510	Ø0.15 wire(Hair root removal)
BS3512	Ø0.15 wire(Hair root removal)
BS5025	Ø0.15 wire(Hair root removal)
BL4015	Ø0.18 wire(Hair root removal)
BL4515	Ø0.18 wire(Hair root removal)
BL5025	Ø0.18 wire(Hair root removal)
E10a	Hemostatic cutting electrode for blepharoplasty (10mm)
E10c	Hemostatic cutting electrode for blepharoplasty (20mm)
I18	Bipolar cord EU Type USA Type

※ Super Fine: Ø 0.2 Tungsten Wire / Fine: Ø 0.25 Tungsten Wire / Regular : Ø 0.3 Tungsten Wire

Instruction Guide

OB/GYN	Operation	Electrode	Monopolar /Bipolar	Time setting	Output level
	Erosion coagulation	E01,E02	Monopolar	Continuous	4~6
	Cervical conization	F01~F05	Monopolar	Continuous	7~8
	LLETZ	G Series	Monopolar	Continuous	7~8
	Bipolar coagulation	Bipolar forcep	Bipolar	Continuous	"2(min) ~10(max) adjusted by forcep active area"
	Cutting	Needle, Loop	Monopolar	Continuous	7~8
		φ6 mm Ball	Monopolar	Continuous	7~8
	Coagulation	φ4 mm Ball	Monopolar	Continuous	4~5
		φ3 mm Ball	Monopolar	Continuous	3~4
Hemostatic cutting	Spear, Blade	Monopolar	Continuous	7~8	

ENT	Operation	Electrode	Monopolar /Bipolar	Time setting	Output level
	Snoring	T16	Bipolar	1 sec	6
	"Chronic hypertonic rhinitis"	T17	Bipolar	1 sec	6
	Exudative otitis media	J10	Monopolar	1/4 sec	5~6
	Cutting	Needle	Monopolar	Continuous	7~8
	Coagulation	φ2 mm Ball	Monopolar	Continuous	2~3
		φ3 mm Ball	Monopolar	Continuous	3~4
	Hemostatic cutting	Blade	Monopolar	Continuous	7~8
	Cutting	Loop (K02)	Monopolar	Continuous	6~8
		Loop (K04)	Monopolar	Continuous	7~8

Surgery (GS • OS • NS)	Operation	Electrode	Monopolar /Bipolar	Time setting	Output level
	Cutting	Needle	Monopolar	Continuous	7~8
	Coagulation	φ4 mm Ball	Monopolar	Continuous	4~5
		φ3 mm Ball	Monopolar	Continuous	3~4
	Hemostatic cutting	Blade	Monopolar	Continuous	7~8
	"First or second degree hemorrhoid"	φ4 mm Ball	Monopolar	1 sec	3~5
		φ3 mm Ball	Monopolar	1 sec	2~3
	Second or third degree early hemorrhoids	T16	Bipolar	1 sec	5~6
	Hair root removal	BS, BL Type	Monopolar	1/2 sec	2~4
	Osmidrosis	C10	Monopolar	1 sec	7~8
	Nervus and freckle	J02	Monopolar	Continuous	3.5
		J03	Monopolar	Continuous	4.5
	"Wart, corn, condyloma,Polyps"	K02,L02	Monopolar	Continuous	6~8
		N01,O02	Monopolar	Continuous	6~8
	Hemostatic coagulation	E03a,E03b	Monopolar	Continuous	3~5
	Cutting	J02,J03	Monopolar	Continuous	7~8
	Hemostatic cutting	E07~E09	Monopolar	Continuous	7~8

Dermatology • Urology	Operation	Electrode	Monopolar /Bipolar	Time setting	Output level
	Hair root removal	BS, B/L Type	Monopolar	1/4 sec or 1/8 sec	2~4
	Osmidrosis	C10	Monopolar	1 sec	7~8
	Nervus and freckle	J01, J02	Monopolar	Continuous	3.5
		J03	Monopolar	Continuous	4.5
	Wart, corn	K01,K02,L02	Monopolar	Continuous	6~8
	Condyloma, polyps	K03	Monopolar	Continuous	6~8
	Hemostatic coagulation	φ2 mm Ball	Monopolar	Continuous	2~3
		φ3 mm Ball	Monopolar	Continuous	3~4
		E06	Monopolar	Continuous	5~6
	Cutting	J01,J02	Monopolar	Continuous	7~8
		J03,J06	Monopolar	Continuous	7~8
	Ophthalmoplasty	J11,J12	Monopolar	Continuous	3~5
	Pimple	BS, BL Type	Monopolar	1 sec	2~4
	Capillary vessel	BS, BL Type	Monopolar	1/2 sec	2~4


! • Dr. Oppel should be used only by well trained doctors. Prior to initial operation, doctors should be fully aware of the operation methods and conditions that are described in the labels attached to the products
 • The guide lines of Output Control, Timer Setting or Operation Time for each symptom described above are standard instruction but may not be fully applicable to all patients in the same way. Therefore operators are requested to do minute adjustments according to each symptom and case

Specification

MODEL NAME	Dr.Oppel ST-501
OUTPUT POWER	MONOPOLAR : 130W ± 20% (Average power on 100Ω load) BIPOLAR : 90W ± 20% (Average power on 50Ω load)
FREQUENCY	4MHz ± 10%
INPUT VOLTAGE	220 / 230 / 240 VAC, 50 / 60Hz
TIME SELECTION	Continuous, 1sec, 1/2sec, 1/4sec, 1/8sec
POWER CONSUMPTION	450 VA + 10% under on maximum load
WEIGHT	10 kg
DIMENSION	Main Unit : 225(W) X 300(L) X 155(H)mm


€ 2195


Standard Accessories



* This specification is changeable without notice for product improvement.

FACTORY -

 Plot No. A-815, MIDC Industrial Area,
Kopar Khairane, Navi Mumbai, Maharashtra 400709

**Analytics Medical
Technologies Pvt. Ltd.**
Office : +91-9322673077 | +91-9892703077
Office : +91-8080321777 | +91-9321548914
E-mail : info@amtmedical.com
Web : www.amtmedical.com